

WARNING

WE RECOMMEND INSTALLATION OF THIS LIGHTING FIXTURE BE DONE BY A LICENSED ELECTRICIAN.
WARNING *** SWITCH OFF THE MAIN ELECTRICAL SUPPLY FROM THE MAIN FUSE BOX/CIRCUIT BREAKER BEFORE INSTALLATION.
INSPECT ITEM CAREFULLY BEFORE ATTEMPTING TO INSTALL. IF THERE IS ANY DAMAGE OR OBVIOUS DEFECT, DO NOT INSTALL. ITEM MAY NOT BE RETURNED ONCE IT HAS BEEN INSTALLED.














CARE AND MAINTENANCE

To clean the outside of the fixture, use a dry or slightly dampened clean cloth (use clean water, never a solvent) to wipe the surface of the fixture.
To clean the inside of the fixture, first disconnect power to the fixture by turning off the circuit breaker or by removing the fuse at the fuse box. Next, use a dry or slightly dampened clean cloth (use clean water, never a solvent) to wipe the interior surface of the fixture.
Do not use any cleaners with chemical, solvents or harsh abrasives. Use only a dry soft cloth to dust or wipe carefully.

NOTICE& IMPORTANT SAFETY INSTRUCTIONS

- * Please make sure that you have all parts indicated before you begin assembly of this item
- * This item should be assembled on a soft surface to prevent scratching the finish during assembly
- * To reduce the risk of fire, electrical shock or injury to persons or property, please follow the guideline below for safe use and installation
- *The external flexible cable or cord of this lamp cannot be replaced
- *If the cord is damaged, the lamp shall be destroyed

Part List and Hardware List

PIECE	DESCRIPTION	PICTURE	QUANTITY	PIECE	DESCRIPTION	PICTURE	QUANTITY
A	Wire connector		3X	H	Mounting screw		2X
B	Wall plug		2X	I	Lamp body		1X
C	Mounting bracket		1X	J	Round tube		1X
D	Ground screw		1X	K	Wire locking device		1X
E	Tapping screw		2X	L	Hex screw		2X
F	Metal plate		2X	M	M3 allen wrench		1X
G	Machine screw		2X				



Model#: JYL7147
Product Dimensions: 23.5"Lx23.5"WX19-78"H



PREPARATION


Before beginning assembly of product, make sure all parts are present. Compare parts with package contents list and hardware contents list. If any part is missing or damaged, do not attempt to assemble the product.

Estimated Assembly Time: 30 minutes.

If there are any questions relating to defects, missing parts, assembly issues, replacements, or device connectivity issues, please send a detailed email to cs@jonathany.com

- 1.Assemble the round tube (J) clock wise onto the lamp body (I) until tight.
- 2. Punch the hole and install the Wall plug (B) to the ceiling.Fix the mounting bracket (C) to the outlet box with tapping screw (E) and mounting screw (G).
- 3. Make wire connections, with wire connectors(A), following the reference chart listed below.

Connect, Hot, Black or Red Outlet Supply Wire to:	Connect, Neutral, White Outlet Supply Wire to:
Black	White
* Parallel Cord (round & smooth)	* Parallel Cord (square & ridged)
Clear, Brown, Gold or Black without Tracer (colored stripes)	Clear, Brown, Gold or Black with Tracer (colored stripes)
Insulated Wire (not green) with copper metal conductor	Insulated Wire (not green) with Silver metal conductor.



*Note: When parallel wire (SPT I & SPT II) is used. The neutral wire is square shaped and ridged and the hot wire will be round in shape and smooth. (See Illustration on left.)

Grounding Instructions:

- a) For installation in the United States: Wrap ground wire from outlet box around green ground screw(D) on mounting bracket, no less than 2" from wire end. Tighten ground screw. If fixture is supplied with a ground wire, connect to outlet ground wire with a wire connector.
 - b) For installation in Canada: If fixture is supplied with ground wire, wrap ground wire around green grounding screw on mounting bracket. Tighten ground screw.
- 4. Carefully remove packaging from fixture,fix the lamp body (I) to mounting bracket(C) using mounting screw(H).
 - 5.Press the expansion piece and adjust the height of the lamp body(I).When the expansion piece fails, Move wire locking device(K) to the desired position and lock it with hex screw (L) and allen wrench (M).
 - 6.Press lock bushing up, then shorten or lengthen fixture wires to the desired length. After all fixture wires are the same height , then loose lock bushing.

ENJOY YOUR LAMP

Compatible Dimmer Model:

Brand	Model No.	Brand	Model No.
TP-LINK	HS220	LEVITON	R11-DSL06-1TW
LUTRON	MACL-153M	LEVITON	R00-RNL06-0TW
LUTRON	DVCL-153P	LEVITON	R68-06674-POT
LUTRON	PD-6WCL	LEVITON	R02-DW6HD-2RW
LUTRON	P-PKG1W-WH-R		

