

RL 9270 RL 9270

ASSEMBLY INSTRUCTIONS

MODEL #: RL9270-6

Only the technical personnel can be allowed to fix and maintain.

IMPORTANT

Be sure that the power is switched off at the electricity mains supply before doing work.

INSTRUCTIONS

1. The raw lampshade (18) will be fixed on the Main body pipe (17) above, it fixed with screw (4) and rotate it into crystal lifting ring (7) (at least 6mm) and tighten with washer (6) & hexagonal nut (5).
 2. The one nut of screw (4) till close to the first nut and then rotate screw batten (13). Make sure screw (4) should go through batten (13).
 3. Fitlet box screws (14) to fix batten (13) on outlet box (1).
 4. Put ring cover (9) from crystal lifting ring (7) and then let the canopy (8) on crystal lifting ring (7). Adjust the crystal lifting ring to a certain

position in the nut to fix on batten (13) in the right position.
 5. Connection (See picture 1): there are one tapping hole & two dimples. Connect supply ground wire (2) on the green ground screw (15) and then put it into the hole. Connect the fixture ground wire (3) with supply ground wire (2) by ring terminal (12). Caution: DO NOT connect ground wire with supply power fixture supply wire (10) with power supply wire (11). Caution: Remember to distinguish the positive and negative charges. (See picture 2)
 6. The ring cover (9) up to the ceiling.
 7. The ring cover (9) on crystal lifting ring and fix canopy (8) as well.
 8. The shade (18) on holder and tightened with out ring bulb in the holder.

PLACEMENT BULB

Do not exceed the maximum wattage.
 lbs recommended: RL9270-6 -E12 6 x 40W Max, Type B.

CLEANING CARE

Wipe with a soft dry cloth.

SAFETY INFORMATION

1. The user must be in rated voltage, and do not touch the bulb with bare hands.
 2. Switch off the electricity supply and allow to cool for 10 minutes before the light bulbs.
 3. External cables have been damaged, PLS change or repair by manufacturer or agency or professional electrician, In order to avoid the danger.

