



1. Assembled the split parts 1 to a completely ring fixture like picture showed, pushed the split parts and fix with bolt screw 2.




2.Let the wire go through the connected tube 3, hang the ring 1 to the junction box 6 with carabiner hook screw connection 4, let the wire go through the junction box 6.




3.Connect all the wires by parallel with splicing connector (9) (all live line-L use one connector, and neutral Line-N use another connector).

4.Let the wire go through the cover $\widehat{\mathcal{T}}$ and hanging ring $\widehat{\otimes}$, rotate ring $\widehat{\otimes}$ to fix the cover $\widehat{\mathcal{T}}$ to the junction box $\widehat{\otimes}$.



5.Connect the canopy ① and the light fixture ⑧ with chain ⑩.



6.Install the bracket to the ceiling junction box with screw ③.

7. Connect the wire to your home line with cap connectors (4).

8.Install the fixture to the bracket with cap nuts 12.

D0154 - 24 / 30

Please read carefully before installation!!!

Note: Please make sure that the electricity is powered off during installation! Only a professional electrician should install this kind of product!